

AN6341N


VTR Capstan Servo Control Circuit

Outline


The AN6341N is an integrated circuit designed for VTR's capstan servo control.

Features

- The function consist of:
 - Phase control circuit
 - Speed control circuit
 - Capstan FG divider ratio change circuit
- Sample & hold system speed control
- Supply voltage either 9V or 12V



Block Diagram




■ Absolute Maximum Ratings (Ta=25°C)

Item	Symbol	Rating	Unit
Supply voltage	V ₁₋₈	14.4	V
Power dissipation	P _D	470	mW
Operating ambient temperature	T _{opr}	-20~+70	°C
Storage temperature	t _{stg}	-40~+150	°C


■ Electrical Characteristics (Ta=25°C)

Item	Symbol	Test Circuit	Condition	min.	typ.	max.	Unit
Circuit current	I ₁	1	V ₁₋₈ =12V	18		34	mA
Sensitivity (PG Amp. Input)	S ₍₁₎	2	V _{CC} =12V	50			mV _{o-p}
Sensitivity (trapezoidal wave input)	S ₍₂₎	3		7			V _{o-p}
Reference voltage (phase trapezoidal wave)	V _{REF(1)}	4		2.7		3.7	V
High-level output voltage (S/H 1)	V _{OH(1)}	5		9			V
Low-level output voltage (S/H 1)	V _{OL(1)}	5				600	mV
Sensitivity (FG Amp. Input)	S ₍₃₎	6		150			mV _{p-p}
Sensitivity (FF2 Switch)	S ₍₄₎	6		5			V
Reference voltage (speed system trapezoidal wave)	V _{REF(2)}	7		2.7		3.7	V
High-level output voltage (S/H 2)	V _{OH(2)}	8		10			V
Low-level output voltage (S/H 2)	V _{OL(2)}	8				1.8	V


Note) Operating Supply Voltage Range V_{cc(oper)} = 8.8~13V



Test Circuit 1 (I₁)




Test Circuit 2 (S₍₁₎)




Note) Pin¹⁵ input
30Hz, 50mV_{op} duty 4%, Rectangular wave

Test Circuit 3 (S₍₂₎)




Note) Pin¹⁵ input (SG-1)
30Hz, 50mV_{op} duty 4% Rectangular wave
Pin¹⁵ input (SG-2)
30Hz, 6V_{op} duty 50% Rectangular wave
However, rise timings for Pin¹⁵ input and Pin¹³ input are the same.

Test Circuit 4 (V_{REF(1)})




Test Circuit 5 (V_{OH(1)}, V_{OL(1)})




Note) Pin¹⁵ input
30Hz, 50mV_{p-p} duty 4% Rectangular wave
Pin¹³ input
30Hz, 6V_{op} duty 50% Rectangular wave
However, rise timings for both signals are the same.
Shift SW₁ to ① when measuring V_s-H
and to ② when measuring V_i-L.

Test Circuit 6 (S₍₃₎, S₍₄₎)




Note) Pin¹⁵ input
360Hz, 100mV_{p-p} Sine wave

Test Circuit 7 (V_{REF(2)})




Note) When the Pin⑯ is set to GND, measure a Pin⑤ voltage. If it is 0V, change over SW₂ and measure the voltage.

Test Circuit 8 (V_{OH(2)}, V_{OL(2)})



Note) Pin⑯ input
360Hz, 150mV_{p-p} Sine wave
Shift SW₃ to ④ when measuring V_{7-H} and to ⑤ when measuring V_{7-L}.

■ Application Circuit



■ Pin

Pin No.	Pin Name	Pin No.	Pin Name
1	V _{cc}	9	Phase Error Voltage
2	FF Select	10	S & H
3	Speed MM	11	Reference Voltage
4	Trapezoid	12	Trapezoid
5	Reference Voltage	13	Reference Input
6	S & H	14	Tracking MM
7	Speed Error Voltage	15	PG Input
8	GND	16	FG Input

Precautions for use

1. A motor start voltage should be 1.8 V or more.
2. For the speed system, change CR of the mono, multi, and trapezoidal wave in accordance with an input frequency

Speed system mono,multi, delay time $T=CR\ln 1.5$

Speed system trapezoidal inclination $T=(V_{cc}/3.2) \cdot CR$

Request for your special attention and precautions in using the technical information and semiconductors described in this book

- (1) If any of the products or technical information described in this book is to be exported or provided to non-residents, the laws and regulations of the exporting country, especially, those with regard to security export control, must be observed.
- (2) The technical information described in this book is intended only to show the main characteristics and application circuit examples of the products. No license is granted in and to any intellectual property right or other right owned by Panasonic Corporation or any other company. Therefore, no responsibility is assumed by our company as to the infringement upon any such right owned by any other company which may arise as a result of the use of technical information described in this book.
- (3) The products described in this book are intended to be used for standard applications or general electronic equipment (such as office equipment, communications equipment, measuring instruments and household appliances).
Consult our sales staff in advance for information on the following applications:
 - Special applications (such as for airplanes, aerospace, automobiles, traffic control equipment, combustion equipment, life support systems and safety devices) in which exceptional quality and reliability are required, or if the failure or malfunction of the products may directly jeopardize life or harm the human body.
 - Any applications other than the standard applications intended.
- (4) The products and product specifications described in this book are subject to change without notice for modification and/or improvement. At the final stage of your design, purchasing, or use of the products, therefore, ask for the most up-to-date Product Standards in advance to make sure that the latest specifications satisfy your requirements.
- (5) When designing your equipment, comply with the range of absolute maximum rating and the guaranteed operating conditions (operating power supply voltage and operating environment etc.). Especially, please be careful not to exceed the range of absolute maximum rating on the transient state, such as power-on, power-off and mode-switching. Otherwise, we will not be liable for any defect which may arise later in your equipment.
 - Even when the products are used within the guaranteed values, take into the consideration of incidence of break down and failure mode, possible to occur to semiconductor products. Measures on the systems such as redundant design, arresting the spread of fire or preventing glitch are recommended in order to prevent physical injury, fire, social damages, for example, by using the products.
- (6) Comply with the instructions for use in order to prevent breakdown and characteristics change due to external factors (ESD, EOS, thermal stress and mechanical stress) at the time of handling, mounting or at customer's process. When using products for which damp-proof packing is required, satisfy the conditions, such as shelf life and the elapsed time since first opening the packages.
- (7) This book may be not reprinted or reproduced whether wholly or partially, without the prior written permission of our company.